



- 12 Volt system
- No. after color states wire size

SWITCH POSITIONS
 P = 30-57 (parking)
 0 = 0-0-0
 1 = 30-15/54 (day)
 2 = 30-57-15/54-INT (night)

- 2. Two beam, 40/45 W bulb
- 3. Speedometer lighting, 2.5 W bulb
- 4. Tachometer lighting, 2.5 W bulb
- 5. Driving beam warning light, 2.5 W bulb
- 6. Generator warning light, 2.5 W bulb
- 7. Switch
- 8. L.H. switch box
- 9. R.H. switch box
- 10. Warning horn (town)
- 11. High voltage coil
- 12. Spark plugs
- 13. Distributor
- 14. Fuses
- 15. Voltage regulator
- 16. Battery
- 17. Starter-generator
- 18. Front and rear stop switch
- 19. Two beam 5/21 W bulb
- 20. Rear direction lights, 21 W bulb
- 21. Flashing unit

- 22. Front direction lights, 21 W bulb
- 23. Anti-noise 3 μ F capacitor
- 24. Anti-noise 3 μ F capacitor
- 25. Anti-noise 4.5 μ F capacitor
- 26. Spark plug cap with metal shielding and 1000 Ω integral resistor
- 27. Distributor rotor arm with integral resistor

| | | |
|---------|----|------------|
| Nero | == | Black |
| Rosso | == | Red |
| Verde | == | Green |
| Grigio | == | Gray |
| Rosa | == | Pink |
| Blu | == | Blue |
| Celeste | == | Light blue |
| Marrone | == | Brown |
| Giallo | == | Yellow |
| Viola | == | Violet |
| Bianco | == | White |

Figure 3-24. Electrical system schematic diagram (U.S. model)